

# Electronic/Glass Fuses

## GGX

- Glass body
- Fast-acting
- 1/4" x 1"



1/2A through 2 1/2A, 250VAC, UL Listed  
3A through 7A, 125V AC, UL Recognized  
8A through 30A, 32V AC, UL Recognized



## Standard Fuse Ampere Ratings

| Catalog Number | Ampere Rating | Volts | I.R. |
|----------------|---------------|-------|------|
| GGX1/2         | 1/2A          | 250V  | 1    |
| GGX3/4         | 3/4A          | 250V  | 1    |
| GGX1           | 1A            | 250V  | 1    |
| GGX1-1/2       | 1-1/2A        | 250V  | 2    |
| GGX2           | 2A            | 250V  | 2    |
| GGX2-1/2       | 2-1/2A        | 250V  | 3    |
| GGX3           | 3A            | 125V  | 3    |
| GGX4           | 4A            | 125V  | 3    |
| GGX5           | 5A            | 125V  | 3    |
| GGX6           | 6A            | 125V  | 3    |
| GGX7           | 7A            | 125V  | 3    |
| GGX8           | 8A            | 32V   | 4    |
| GGX10          | 10A           | 32V   | 4    |
| GGX12          | 12A           | 32V   | 4    |
| GGX15          | 15A           | 32V   | 4    |
| GGX20          | 20A           | 32V   | 4    |
| GGX25          | 25A           | 32V   | 4    |
| GGX30          | 30A           | 32V   | 4    |

1. 250VAC @ 35A I.R./125VAC @ 10kA I.R.
2. 250VAC @ 100A I.R./125VAC @ 10kA I.R.
3. 125VAC @ 10kA I.R.
4. 32VAC

## GAB

- Ceramic body
- Fast-acting
- 1/4" x 1-1/4"



1/8A through 15A, 250VAC,  
UL Listed and CSA Certified  
20A through 30A, 250/125VAC, UL Recognized



## Standard Fuse Ampere Ratings

| Catalog Number | Ampere Rating | Volts | I.R. |
|----------------|---------------|-------|------|
| GAB1/8         | 1/8A          | 250V  | 1    |
| GAB1/4         | 1/4A          | 250V  | 1    |
| GAB3/8         | 3/8A          | 250V  | 1    |
| GAB1/2         | 1/2A          | 250V  | 1    |
| GAB3/4         | 3/4A          | 250V  | 1    |
| GAB1           | 1A            | 250V  | 1    |
| GAB2           | 2A            | 250V  | 2    |
| GAB2-1/2       | 2-1/2A        | 250V  | 2    |
| GAB3           | 3A            | 250V  | 2    |
| GAB4           | 4A            | 250V  | 3    |
| GAB5           | 5A            | 250V  | 3    |
| GAB6           | 6A            | 250V  | 3    |
| GAB7           | 7A            | 250V  | 3    |
| GAB8           | 8A            | 250V  | 3    |
| GAB10          | 10A           | 250V  | 3    |
| GAB12          | 12A           | 250V  | 4    |
| GAB15          | 15A           | 250V  | 4    |
| GAB20          | 20A           | 250V  | 5    |
| GAB25          | 25A           | 125V  | 6    |
| GAB30          | 30A           | 125V  | 6    |

1. 250VAC @ 35A I.R./125VAC @ 10kA I.R.
2. 250VAC @ 100A I.R./125VAC @ 10kA I.R.
3. 250VAC @ 200A I.R./125VAC @ 10kA I.R.
4. 250VAC @ 750A I.R./125VAC @ 10kA I.R.
5. 250V/125VAC @ 400A I.R.
6. 125VAC @ 400kA I.R.